

PREMIUM

CZUJNIKI RUCHU/MOTION DETECTORS

CZUJNIK RUCHU BLUETOOTH ZHAGA

/ BLUETOOTH ZHAGA MOTION SENSOR



- detektor ruchu Bluetooth, programowalny za pomocą aplikacji Tuya Smart,
- możliwość programowania wielu czujników z jednego urządzenia,
- kompatybilny z gniazdem Zhaga Book 18 – dedykowany do opraw LED ANICA,
- max wysokość montażu: 12 m,
- kąt/zasięg detekcji: 360° / max. 5 m,
- czułość detekcji: niska, średnia, wysoka,
- czas utrzymania pracy czujnika: od 5 s do 60 min,
- moc w trybie czuwania: 10-30%,
- długość trwania trybu czuwania: od 1 min do 8h, nieograniczony.

- Bluetooth motion detector, programmable via the Tuya Smart app,
- the ability to program multiple sensors from a single device,
- compatible with Zhaga Book 18 socket – dedicated to LED ANICA fixtures,
- max. mounting height: 12 m,
- detection angle/range: 120 degrees/max. 4 m,
- detection sensitivity: low, medium, high,
- sensor hold time: from 5 seconds to 60 minutes,
- standby power mode: 10-30%,
- standby duration: from 1 minute to 8 hours, unlimited, unlimited.

MODEL	SKU	KOLOR	WYMIARY [mm]	WAGA NETTO [kg]	PAKOWANIE [szt.]	KOD EAN
MODEL	SKU	COLOR	SIZE [mm]	NET WEIGHT [kg]	PACKING [pcs]	BARCODE
CZUJNIK RUCHU BLUETOOTH ZHAGA	003778	CZARNY BLACK	Ø 50,4x35	0,03	1	5902201387124

